

CONDITIONED SHORT-CIRCUIT CURRENT – GDA/MERLIN GERIN- SCHNEIDER

[kA eff. 1"] (400/440 V c.a.)

| Switch model | GDA (In) | | | | | | | | | | |
|--------------|----------|-------|-------|-------|-------|-------|-------|-------|--------|--------|--------|
| | 63 A | 100 A | 160 A | 250 A | 400 A | 500 A | 630 A | 800 A | 1000 A | 1250 A | 1600 A |
| NSX100 B | 10 | 10 | 10 | 13 | 27 | 29 | 33 | 35 | 40 | 42 | 50 |
| NSX100 F | 10 | 10 | 10 | 13 | 27 | 29 | 33 | 35 | 40 | 42 | 50 |
| NSX100 N | 10 | 10 | 10 | 13 | 27 | 29 | 33 | 35 | 40 | 42 | 50 |
| NSX100 H | 10 | 10 | 10 | 13 | 27 | 29 | 33 | 35 | 40 | 42 | 50 |
| NSX100 S | 10 | 10 | 10 | 13 | 27 | 29 | 33 | 35 | 40 | 42 | 50 |
| NSX100 L | 10 | 10 | 10 | 13 | 27 | 29 | 33 | 35 | 40 | 42 | 50 |
| NSX100 R | 10 | 10 | 10 | 13 | 27 | 29 | 33 | 35 | 40 | 42 | 50 |
| NSX160 B | | | 10 | 13 | 27 | 29 | 33 | 35 | 40 | 42 | 50 |
| NSX160 F | | | 10 | 13 | 27 | 29 | 33 | 35 | 40 | 42 | 50 |
| NSX160 N | | | 10 | 13 | 27 | 29 | 33 | 35 | 40 | 42 | 50 |
| NSX160 H | | | 10 | 13 | 27 | 29 | 33 | 35 | 40 | 42 | 50 |
| NSX160 S | | | 10 | 13 | 27 | 29 | 33 | 35 | 40 | 42 | 50 |
| NSX160 L | | | 10 | 13 | 27 | 29 | 33 | 35 | 40 | 42 | 50 |
| NSX160 R | | | 10 | 13 | 27 | 29 | 33 | 35 | 40 | 42 | 50 |

| | | | | | | | | | | | |
|----------|--|--|--|-----|-----|-----|-----|-----|-----|-----|-----|
| NSX250 B | | | | 26 | 27 | 29 | 33 | 35 | 40 | 42 | 50 |
| NSX250 F | | | | 36 | 36 | 36 | 36 | 36 | 40 | 42 | 50 |
| NSX250 N | | | | 50 | 50 | 50 | 50 | 50 | 50 | 50 | 50 |
| NSX250 H | | | | 70 | 70 | 70 | 70 | 70 | 70 | 70 | 70 |
| NSX250 S | | | | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 |
| NSX250 L | | | | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 |
| NSX250 R | | | | 100 | 100 | 100 | 100 | 100 | 100 | 100 | 100 |
| NSX400 F | | | | | 36 | 36 | 36 | 36 | 40 | 42 | 50 |
| NSX400 N | | | | | 50 | 50 | 50 | 50 | 50 | 50 | 50 |
| NSX400 H | | | | | 70 | 70 | 70 | 70 | 70 | 70 | 70 |
| NSX400 S | | | | | 100 | 100 | 100 | 100 | 100 | 100 | 100 |
| NSX400 L | | | | | 150 | 150 | 150 | 150 | 150 | 150 | 150 |
| NSX400 R | | | | | 200 | 200 | 200 | 200 | 200 | 200 | 200 |
| NSX630 F | | | | | | 36 | 36 | 36 | 40 | 42 | 50 |
| NSX630 N | | | | | | 50 | 50 | 50 | 50 | 50 | 50 |
| NSX630 H | | | | | | 70 | 70 | 70 | 70 | 70 | 70 |
| NSX630 S | | | | | | 100 | 100 | 100 | 100 | 100 | 100 |
| NSX630 L | | | | | | 150 | 150 | 150 | 150 | 150 | 150 |
| NSX630 R | | | | | | 200 | 200 | 200 | 200 | 200 | 200 |
| NSX630bN | | | | | | | 36 | 36 | 40 | 42 | 50 |
| NS630bH | | | | | | | 36 | 36 | 40 | 42 | 50 |
| NS630bL | | | | | | | 110 | 110 | 110 | 110 | 110 |
| NS630bLB | | | | | | | 180 | 180 | 180 | 180 | 180 |
| NS800N | | | | | | | | 36 | 40 | 42 | 50 |

| | | | | | | | | | | | |
|---------|--|--|--|--|--|--|--|-----|-----|-----|-----|
| NS800H | | | | | | | | 36 | 40 | 42 | 50 |
| NS800L | | | | | | | | 130 | 130 | 130 | 130 |
| NS800LB | | | | | | | | 200 | 200 | 200 | 200 |
| NS1000N | | | | | | | | | 40 | 42 | 50 |
| NS1000H | | | | | | | | | 40 | 42 | 50 |
| NS1000L | | | | | | | | | 130 | 130 | 130 |
| NS1250N | | | | | | | | | | 45 | 50 |
| NS1250H | | | | | | | | | | 45 | 50 |
| NS1600N | | | | | | | | | | | 50 |
| NS1600H | | | | | | | | | | | 55 |